

## CONTROL UNIT FOR ROLL-A-MOTORS



### TECHNICAL SPECIFICATION

Voltage	: 110 or 230 : 1 phase : 50/60 Hz 220 or 400 : 3 phase : 50/60 Hz
Power output	: 2200 watts for 1 phase 3000 watts for 3 phase
Dimensions	: L 56 cm x W 36 cm x H 18 cm L 22" x W 14 11/64" x H 7 5/64"
Weight	: 15 kg
Optional	: Printer

**Transformer to 42 volts**

### STANDARD FITTINGS

- Remote control (24 volts).
- Digital read-out for programming.
- Digital read-out for torque.
- Reverse time setting 0 to 60 seconds.
- Interval time setting 0 to 60 seconds.
- Automatic phase corrector for 3 phase models.
- Flat panel, easy clean push buttons.
- Carrying handle.
- RS 232 connector for interface with PC for read-out.

### ROLL-A-MOTOR CONTROL UNIT WITH TRANSFORMER

